

Uši



How to use Uši

You will need a recorder or a sound card with plug-in power input. Usually this is represented by “mic in” mini-jack input.

- 1. Plug Uši into your recorders “mic in”.
- 2. Make sure that plug-in power is on.
- 3. On some recorders this needs to be set up using internal menus. Consult the recorders manual if you’re not sure.
- 4. Set your gain to appropriate levels and enjoy!

[How to attach clips to Uši microphones](#)

Technical specifications

Matched stereo pair of pre-polarized condenser microphones	
Cable	1.5 m (for each mic) with 3.5 mm (1/8”) jack
Impedance	2.4 kΩ at 1kHz
Maximum input pressure level	~122 dB SPL
Sensitivity	-28 dB at 1kHz (±3 dB)
Self-noise	14-17 dBA

From:

<http://knowledge.lom.audio/> - **LOM knowledge base**

Permanent link:

<http://knowledge.lom.audio/manuals/usi?rev=1470871633>

Last update: **2016/08/11 01:27**

