

Uši microphone comparison

Model	Uši Pro	Ucho Pro	Uši
Description	Matched phantom powered, pre-polarized condenser microphones	Phantom powered, pre-polarized condenser microphone	Matched stereo pair of pre-polarized condenser microphones
Operating voltage	24-48V (P48 phantom power)	28-48V (P48 phantom power)	2-10V (plug-in power)
Cable	2 x 1.5 m with 2.5 mm diameter	1.5 m with 2.5 mm diameter	1.5 m with 2.5 mm diameter
Maximum input pressure level	~122 dB SPL	~122 dB SPL	~122 dB SPL
Sensitivity	-28 dB at 1kHz (±3 dB)	-28 dB at 1kHz (±3 dB)	-28 dB at 1kHz (±3 dB)
Self-noise	~14 dBA	~14 dBA	~14 dBA
Output	2x XLR-3M balanced, transformer-less, floating	XLR-3M balanced, transformer-less, floating	3.5mm (1/8") jack
Output impedance	30-50 Ω	30-50 Ω	2.4 kΩ
Power consumption	~3mA per pin per channel	~3mA per pin	~700µA per channel
Model	mikroUši Pro	mikroUcho Pro	mikroUši
Description	Matched phantom powered, pre-polarized condenser microphones	Phantom powered, pre-polarized condenser microphone	Matched stereo pair of pre-polarized condenser microphones
Operating voltage	24-48V (P48 phantom power)	28-48V (P48 phantom power)	2-10V (plug-in power)
Cable	2 x 1.5 m with 2.1 mm diameter	1.5 m with 2.1 mm diameter	2 x 1.5 m with 2.1 mm diameter
Maximum input pressure level	~115 dB SPL	~115 dB SPL	~115 dB SPL
Sensitivity	-32 dB at 1kHz (±3 dB)	-32 dB at 1kHz (±3 dB)	-32 dB at 1kHz (±3 dB)
Self-noise	~20 dBA	~20 dBA	~20 dBA
Output	2x XLR-3M balanced, transformer-less, floating	XLR-3M balanced, transformer-less, floating	3.5mm (1/8") jack
Output impedance	30-50 Ω	30-50 Ω	1.6 kΩ
Power consumption	~3mA per pin per channel	~3mA per pin	~550µA per channel

From:
<http://knowledge.lom.audio/> - LOM knowledge base

Permanent link:
http://knowledge.lom.audio/manuals/usi_comparison?rev=1518466690

Last update: **2018/02/12 21:18**

